

AMENDMENTS TO THE CLAIMS

Please amend Claims 1, 3-5, 9-12, 16, 18, and 19 as follows, without prejudice or disclaimer to continued examination on the merits:

1. (Currently Amended) A method of testing a bit error rate for each of a plurality (N) of optical communication channels, N being greater than 2, in a wavelength division multiplexed optical communication system having N optical transmitters communicating to N optical receivers via N communication channels, the N optical receivers being co-located with each other and with the N optical transmitters for testing, the method comprising:

cascading said N optical communication channels such that an electrical output of an optical receiver i for an optical communication channel i is connected to an input of an optical transmitter i + 1 for an optical communication channel i + 1, for all values of i from one to N-1, so as to form a continuous cascade of a co-located plurality of optical transmitter/receiver pairs;

supplying a bit error rate test signal from a bit error rate tester to an input for a first optical transmitter for a first optical communication channel;

supplying the bit error rate test signal from an output of optical receiver N to the bit error rate tester;

detecting errors in the bit error rate test signal received by the bit error rate tester and calculating therefrom a measured system bit error rate;

comparing the measured system bit error rate with a predetermined system bit error rate threshold;

monitoring a ~~signal-quality~~ signal-to-noise parameter (Q) for the bit error rate test signal at each of the N optical transmitters and N optical receivers when the measured system bit error rate is greater than the predetermined system bit error rate threshold to thereby determine which of the N optical communication channels has an associated bit error rate value that is greater/less than a specified bit error rate value; and

comparing the monitored Q with a predetermined Q threshold, wherein the predetermined Q threshold corresponds to the predetermined system bit error rate threshold.

2. (Original) The method of claim 1, wherein said predetermined system bit error rate is equal to the specified bit error rate for each of N optical communication channels.
3. (Currently Amended) The method of claim 1, ~~wherein said monitoring said signal quality includes a bit parity check~~ further comprising performing a bit parity check at each of the N optical transmitters and N optical receivers.
4. (Currently Amended) The method of claim 3, wherein said ~~monitoring~~ performing includes monitoring a bit interleave parity for said bit parity check on each electrical signal in the N optical transmitter/receiver pairs.
5. (Currently Amended) A method for performing a bit error rate test for a plurality of optical communication channels of a wavelength division optical communication system having transmitters and receivers, the transmitters being co-located with each other and with the receivers for testing, comprising:
 - supplying a bit error rate test signal from a bit error rate tester to an input for a first optical transmitter for a first optical communication channel of said plurality of optical communication channels arranged in a continuous cascade of a co-located plurality of transmitter/receiver pairs;
 - receiving the bit error test signal at the bit error rate tester from a final optical receiver;
 - detecting a measured bit error rate; and
 - identifying at least one faulty communication channel from said plurality of optical communication channels by performing a bit parity check and a signal-to-noise (Q) calculation for each transmitter/receiver pair because the measured bit error rate is greater than a predetermined system bit error rate threshold.
6. (Previously Presented) The method of claim 5, further comprising monitoring a signal quality for the at least one faulty communication channel using an internal performance monitor.
7. (Previously Presented) The method of claim 6, wherein said internal performance monitor checks a signal transmitted through the at least one faulty communication channel.

8. (Previously Presented) The method of claim 5, further comprising passing said bit error rate test signal through said plurality of optical communication channels.

9. (Currently Amended) A system for testing optical communication channels for wavelength division multiplexed optical communication using transmitters and receivers, the transmitters being co-located with each other and the receivers for testing, comprising:

a bit error rate tester to generate a bit error rate test signal, wherein the bit error rate test signal is transmitted over a plurality of optical communication channels arranged in a continuous cascade of a co-located plurality of optical transmitter/receiver pairs;

said tester determining a measured bit error rate, wherein said tester determines whether said measured bit error rate is greater than a predetermined bit error rate threshold for said plurality of optical communication channels; ~~and~~

a diagnostic analyzer to analyze diagnostic output signals from said transmitters and said receivers and to identify at least one faulty communication channel from said optical transmitter/receiver pairs using a bit parity check because said measured bit error rate is greater than said predetermined bit error rate threshold; and

an internal performance monitor on said transmitters and said receivers, wherein said internal performance monitor monitors bit errors and signal-to-noise parameters (Qs) of signals between said transmitters and said receivers.

10. (Currently Amended) The system of claim 9, ~~further comprising an~~ wherein said internal performance monitor is coupled to said diagnostic analyzer.

11. (Currently Amended) The system of claim 10, wherein said internal performance monitor ~~includes~~ comprises an error monitoring unit.

12. (Currently Amended) The method of claim 1, wherein said monitoring monitors a received signal ~~quality~~ Q for the bit error rate test signal supplied by the bit error rate tester, as the bit error rate test signal is propagating from the input for the first optical transmitter to the output of the optical receiver N.

13. (Previously Presented) The method of claim 1, further comprising:

indicating that a bit error rate for each of the N optical communication channels is less than a specified bit error rate value when the measured system bit error rate is less than or equal to the predetermined system bit error rate threshold.

14. (Previously Presented) The method of claim 1, wherein the monitoring of the bit error rate test signal is performed at an input of each of the N optical transmitters and N optical receivers.

15. (Previously Presented) The method of claim 5, wherein the plurality of optical communication channels include three or more optical communication channels that are cascaded.

16. (Currently Amended) The method of claim 5, wherein the identifying at least one faulty communication channel monitors the signal ~~quality~~ Q of the bit error rate signal, as the bit error rate test signal is propagating from the input for the first optical transmitter through the continuous cascade of transmitter/receiver pairs.

17. (Previously Presented) The method of claim 9, wherein the plurality of optical communication channels includes three or more optical communication channels that are cascaded.

18. (Currently Amended) The method of claim 9, wherein the diagnostic analyzer is configured to analyze the diagnostic output signals from said transmitters and receivers in response to monitoring a signal ~~quality~~ Q of the bit error rate signal input to each of said transmitters and said receivers.

19. (Currently Amended) The method of claim 18, wherein each of said transmitters and said receivers is configured to monitor the signal ~~quality~~ Q of the bit error rate signal supplied by the bit error rate tester, as the bit error rate test signal is propagating from the input of the first optical communication channel to the final optical receiver.

20. (Previously Presented) The method of claim 1, wherein the optical transmitters and optical receivers for the N optical communication channels are co-located.

21. (Previously Presented) The method of claim 5, wherein the plurality of optical communication channels are arranged in the continuous cascade by connecting electrical outputs of optical receivers to inputs of optical transmitters in the plurality of transmitter/receiver pairs.

22. (Previously Presented) The system of claim 9, wherein the plurality of optical communication channels are arranged in the continuous cascade by connecting electrical outputs of optical receivers to inputs of optical transmitters in the plurality of transmitter/receiver pairs.